การติดตั้งเครื่องพิมพ์ Samsung M3820ND

สิ่งที่ต้องเตรียมก่อนการติดตั้ง คือ

1.แผ่นซีดีไดร์เวอร์ หรือเข้าไปที่ Run หรือ Search

\\192.168.10.101\Drivers\[--Printer--]\SamsungSL-M3820ND

2.หมายเลข IP ADDRESS เครื่องพิมพ์ Samsung M3820ND ที่สติกเกอร์ติดที่ ตัวเครื่องว่าหมายเลขอะไร

3.เมื่อพร้อมก็ทำการใส่แผ่นซีดี



4.แล้วคลิกเปิดไฟล์ setup



5.เมื่อเริ่มที่หน้าเมนูคลิกเลือกที่ช่อง

have reviewed and accept the installation agreements> Next

#	Samsung M332x 382x 402x Series	
1. Welcome		
2. Connecting Printers	Samsung Printer Pro<i>Xpress</i>	
3. Select Software	M332x M382x M402x series	
4. Installation		
5. Finish		
	Before installing any software, you must accept the End User License Agreement and customize your settings regarding the Internet Connection Usage Options. Click each link to review detailed information.	
	The software End User License Agreement (Required) Internet Connection Usage Options The software may use an internet connection to transmit data to check for software updates and to provide relevant benefits. For information about internet connection usage, dick "Internet Connection Usage Options".	
	✓ I have reviewed and accept the installation agreements.	
	CD version: 1.16 (12//12013)	
View User's Guide	Next > Cancel	

6.คลิกเลือกที่ช่อง Network connection>Next

2	Samsung M332x 382x 402x Series	×
1. Welcome 2. Connecting Printers	Printer Connection Type	
3. Select Software	Select how the printer will be connected to your computer or network.	
4. Installation		
5. Finish	USB connection Connect the printer to this computer using a USB cable.	
	Network connection Connect the printer to the same network as this computer. If your printer is already connected to the network, the installer will detect the printer.	
	Wireless network connection Connect the printer to the same wireless network as this computer. If your printer is not connected to the wireless network, the installer will help you set up the wireless network. This is only available for printers that support wireless networking.	
	Select if you want to install the software without connecting the printer.	
	< Back Next > Cancel	

7.คลิกเลือกที่ช่อง Os,I will set up printer's network.> Next



8. คลิกเลือกที่ช่อง

lect if you want to set the printer's IP Address manually. > Next

2	Samsung M332x 382x 402x Series
1. Welcome	
2. Connecting Printers	Connect the printer using an ethernet cable
3. Select Software	Turn on your printer and then connect the ethernet cable to your printer.
4. Installation	After ensuring that the printer is ready, tack frext > . Setup will search for your printer of the network.
5. Finish	
	For advanced users:
	Select if you want to set the printer's IP Address manually.
	< Back Next > Cancel

9.โปรแกรมจะเริ่มการค้นหาเครื่องพิมพ์

49 (A)	Samsung M332x 382x 402x Series	×
1. Welcome		
2. Connecting Printers	Searching for Printers	
3. Select Software	Setup is searching for network-connected printers.	
4. Installation		
5. Finish		
	Searching for available printers, please wait	
	< Back Next > Cancel	

10.เมื่อโปรแกรมค้นหาเครื่องพิมพ์เจอคลิกเลือกที่เครื่องพิมพ์ ดังรูป

#	Samsung	M332x 382x 402x Serie	es	×
1. Welcome 2. Connecting Printers 3. Select Software	Set IP Address You can set or change IP A	Address for the network printer.		
4. Installation	Printer Name	IP Address	MAC Address	
5. Finish	SEC30CDA7144FCF	10.16.10.5	30CDA7144F0	CF
	Note : Select a printer to b	e set with a specific IP address	from the list and set the IP Ad	Search Again dress below.
	MAC Address:	30CDA7144FCF		
	IP Address (IPV4):	10 . 16 . 10 . 5		
	Subnet Mask:	255 . 255 . 255 . 0		
	Gateway:	10 . 16 . 10 . 1		Apply
			< Back Next >	Cancel

11.คลิก Next

- 문	Samsung M332x 382x 402x Se	ries			×
1. Welcome					
2. Connecting Printers	Select Software to Install				
3. Select Software	Select the software to install.				
4. Installation					_
5. Finish		Setup type:	Recommended		~
	Software Name	Sta	itus	Version	
	Samsung M332x 382x 402x Series printer driver Samsung Easy Printer Manager Samsung Easy Wireless Setup Check for the latest software updates from the Sam	Not insta Not insta Not insta sung server. tiver	alled yet alled yet alled yet	3.12.29.00:21 1.03.72.00 3.60.40.0	
		< Back	Next >	dvanced Options	

12.โปรแกรมจะเริ่มทำการติดตั้ง

	Samsung M332x 382x 402x Series
1. Welcome 2. Connecting Printers 3. Select Software 4. Installation 5. Finish	В С В С В С В С В С В С В С В С В С В С
	Don't take chances! Use genuine Samsung toner! Genuine Samsung toner always delivers best value, dean and crisp images, guaranteed performance and eco-friendly printing. Get real value and true performance with genuine Samsung toner!
	User's Guide files are being copied
	< Back Next > Cancel

13.คลิกเลือกที่ ดังรูป 🗌 Print a test page

และ Enable Printer Status Monitor >Finish



14.เมื่อเครื่องพิมพ์ทำการพิมพ์กระดาษที่ทดสอบ เป็นการสิ้นสุดการติดตั้ง

	Samsung M332x 382x 402x Series		
	1. Welcome		
i.	2. Connecting Printers	Setup Completed	
	3. Select Software	Your Samsung M332x 382x 402x Series Software installation has been completed.	
	4. Installation 5. Finish	✓ Print a test page Select to print a test page after installation.	
		Start Easy Eco Driver before printing job Easy Eco Driver enables you to see a print preview and save toner/paper by adjusting print options.	
		✓ Enable Printer Status Monitor	
		Software for monitoring printer status from your computer.	
		Samsung M332x 382x 402x Series	
		Finish	

จัดทำโดย นายธนากร แนวพิชิต

28 สิงหาคม 2557